



Photo 6 shows installation for one TV set in RV. So simple, unscrew cable from wall unit to TV at wall unit and screw into one of the two “TV/Radio” outlets on ET. Then the white cable supplied with ET goes from “aerial” outlet on ET to wall unit.



Photo 7 shows how to connect for multiple TV sets in van & wall plate needs to be taken off wall to get to where cable to other TV sets is screw into back of wall plate In photo 7 this is the right hand cable to multiple TV sets. The left hand cable is the cable coming from the roof and must not be touched.



Photo 8 shows where we have drilled a 12mm hole through the wall plate so that the unscrewed multiple TV cable, if long enough can be pulled through to reach the easy tune unit. The cable then goes to the second “TV/Radio” outlet on ET. Set up for TV1 is the same as photo 6 above.



Photo 9 shows parts that can be purchased and installed in wall plate if the cable is not long enough to be pulled through so in this case another short cable will be needed to go from front of wall plate to ET. These parts can be purchased from Happy Wanderer. For this scenario only drill 10mm hole.

WARNING: before drilling 12 or 10mm hole, mark spot for hole and re fit plate temporarily to stop plate spinning whilst drilling



Photo 10

This is an example of the finished installation of ET for multiple TV sets in RV. Because of short length of cable out of wall unit we had to mount ET sideways but this does not affect use of product. In this example, the wall plate had a spacer so we could drill a 12mm hole through the spacer.